

Make	Model	Function	# Lamps	Rating	Part #	Notes
Kenwood	KA-5700/5750	Meters	2	8v/300ma	B30-0132-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KA-6100/6150	Meters	2	8v/300ma	B30-0132-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KA-9100/9150	Meters	2	8v/150ma	B30-0124-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-3600/3060	Dial	5	8v, 300ma	B30-0069-05	10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-3600/3060	Indicators	1	8v, 50ma	?B30-0064-05?	4mm bulb in rubber grommet base and two wires.
Kenwood	KR-3600/3060	Meters	2	8v, 200ma	B30-0068-05	10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-4400	Dial	3	8v, 300ma	B30-0069-05	10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-4400	Indicators	1	8v, 50ma	B30-0064-05	4mm bulb in rubber grommet base and two wires.
Kenwood	KR-4400	Meters	1	8v, 200ma	B30-0068-05	10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-4600/4060	Dial	5	8v, 300ma	B30-0069-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-4600/4060	Meters	2	8v, 200ma	B30-0068-05	10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-5400	Dial	4	8v, 300ma	B30-0069-05	10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-5400	Indicators	1	8v, 50ma	B30-0064-05	4mm bulb in rubber grommet base and two wires.
Kenwood	KR-5400	Meters	1	8v, 200ma	B30-0068-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-5600/5060	Dial	5	8v, 300ma	B30-0069-05	10mm globe bulb in rubber grommet base with 2 wires.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Kenwood	KR-5600/5060	Meters	2	8v, 200ma	B30-0068-05	10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-6400	Dial	4	8v, 300ma	B30-0069-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-6400	Indicators	1	8v, 50ma	B30-0064-05	4mm bulb with in rubber grommet base and two wires.
Kenwood	KR-6400	Meters	2	8v, 150ma		4mm(?) lamp in rubber grommet base and two wires.
Kenwood	KR-6600/6060	Dial	6	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	KR-6600/6060	Indicators	6	8v, 50ma	B30-0077-05	4mm bulb with rubber base slides over two pins.
Kenwood	KR-6600/6060	Meters	1	8v, 300ma	B30-0069-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-7340	Dial	5	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	KR-7340	Indicators	7	8v, 50ma	B30-0084-05	Rubber base slides over two pins. Minature version of Dial Lamp?
Kenwood	KR-7340	Meters(tuning)	1	8v, 150ma		4mm lamp in rubber grommet base with 2 wires.
Kenwood	KR-7340	Meters(VU)	4	8v, 200ma		10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-7400	Dial	5	8v, 300ma	B30-0069-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-7400	Indicators	1	8v, 50ma	?B30-0064-05?	5mm(?) lamp in rubber grommet base and two wires.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Kenwood	KR-7400	Meters	2	8v, 200ma	B30-0068-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-7600/7060	Dial	6	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	KR-7600/7060	Indicators	6	8v, 50ma	B30-0077-05	4mm bulb with rubber base slides over two pins.
Kenwood	KR-7600/7060	Meters	1	8v, 300ma	B30-0069-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-8340	Dial	5	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	KR-8340	Indicators	7	8v, 50ma	B30-0084-05	Rubber base slides over two pins. Minature version of Dial Lamp?
Kenwood	KR-8340	Meters(tuning)	1	8v, 150ma		4mm lamp with 10mm bulb in rubber grommet base with 2 wires.
Kenwood	KR-8340	Meters(VU)	4	8v, 200ma		10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-9340	Dial	5	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	KR-9340	Indicators	7	8v, 50ma	B30-0084-05	Rubber base slides over two pins. Minature version of Dial Lamp?
Kenwood	KR-9340	Meters(tuning)	2	8v, 150ma		4mm lamp in rubber grommet base with 2 wires.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Kenwood	KR-9340	Meters(VU)	4	8v, 200ma		10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-9400	Dial	5	8v, 300ma	B30-0069-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-9400	Meters	2	8v, 200ma	B30-0068-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KR-9600/9060	Dial	6	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a". Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	KR-9600/9060	Indicators	9	8v, 50ma	B30-0077-05	4mm bulb with rubber base slides over two pins.
Kenwood	KR-9600/9060	Meters	4	8v, 200ma	B30-0068-05	10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KT-5500/5550	Dial	2	8v, 300ma		10mm globe bulb in rubber grommet base with 2 wires. Wired in series with meter. All three must be replaced unless exact replacement used.
Kenwood	KT-5500/5550	Meters	1	8v, 300ma		10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial. All three must be replaced unless exact replacement used.
Kenwood	KT-6500/6550	Dial	2	8v, 300ma		10mm globe bulb in rubber grommet base with 2 wires. Wired in series with meter. All three must be replaced unless exact replacement used.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Kenwood	KT-6500/6550	Meters	1	8v, 300ma		10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial. All three must be replaced unless exact replacement used.
Kenwood	KT-7300	Dial+Meter	4	8v, 300ma		10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	KT-7500/7550	Dial	2	8v, 300ma		10mm globe bulb in rubber grommet base with 2 wires. Wired in series with meter. All three must be replaced unless exact replacement used.
Kenwood	KT-7500/7550	Meters	1	8v, 300ma		10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial All three must be replaced unless exact replacement used.
Kenwood	KT-8005	Dial	4	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	KT-8005	Indicators	5	8v, 50ma	B30-0064-05(?)	4mm lamp in rubber grommet base with 2 wires.
Kenwood	KT-8005	Meters	2	8v, 150ma		4mm lamp in rubber grommet base with 2 wires.
Kenwood	KT-8007	Dial	4	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Kenwood	KT-8007	Indicators	5	8v, 50ma	B30-077-05	Rubber base slides over two pins. Double check this - Part# per Service manual but different than KT-8005.
Kenwood	KT-8007	Meters	2	8v, 300ma(?)		
Kenwood	KT-8300	Dial	2	8v,300ma	B30-0116-05	Fuse lamp
Kenwood	KT-8300	Meters	3	8v,300ma	B30-0123-05	
Kenwood	L-07t	Dial	4	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	L-07t	Meters	2	8v, 200(?)ma		10mm globe bulb in rubber grommet base with 2 wires.
Kenwood	L-07tii	Dial	4	8v, 300ma	B30-0075-05	10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Sansui TU-717.
Kenwood	L-07tii	Meters	2	8v, 200(?)ma		10mm globe bulb in rubber grommet base with 2 wires.
Sansui	3900Z	Dial	1	8v,300ma	04007600	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	4900Z	Dial	1	8v,300ma	04007600	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	5900Z	Dial	1	8v,300ma	04007600	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	7900Z	Dial	1	8v,300ma	04007600	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	7900Z	Volume Indicator	1	8v,150ma	04006600	
Sansui	8900ZDB	Dial	1	8v,300ma	04007600	10mm globe bulb in rubber grommet base with 2 wires.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Sansui	8900ZDB	Volume Indicator	1	8v,150ma	04006600	
Sansui	9900Z	Dial	1	8v,300ma	04007600	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	9900Z	Volume Indicator	1	8v,150ma	04006600	
Sansui	G-2000	Dial	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial. Both must be replaced unless exact replacement used.
Sansui	G-2000	Meter	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial. Both must be replaced unless exact replacement used.
Sansui	G-22000	Dial	2	8v,300ma	0400650	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-22000	Meter	2	8v,300ma	0400650	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-3000	Dial	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial. Both must be replaced unless exact replacement used.
Sansui	G-3000	Meter	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial. Both must be replaced unless exact replacement used.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Sansui	G-33000	Dial	2	8v,300ma	0400650	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-33000	Meter	2	8v,300ma	0400650	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-3500/301	Dial	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial. Both must be replaced unless exact replacement used.
Sansui	G-4500/401	Meter	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires. Wired in series with dial. Both must be replaced unless exact replacement used.
Sansui	G-4700	Dial	1	8v,300ma	0500710	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-5000	Dial	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-5000	Meter	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-5500	Dial	1	8v,300ma	0400650	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-5500	Meter	1	8v,300ma	0400650	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-5700	Dial	1	8v,300ma	0500710	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-6000	Dial	2	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-6000	Meter	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Sansui	G-6700	Dial	2	8v,300ma	0500710	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-7000/701	Dial	2	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-7000/701	Meter	1	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-7500	Dial	1	8v,300ma	0400650	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-7500	Meter	2	8v,300ma	0400650	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-7700	Dial	2	8v,300ma	0500710	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-8000/801	Dial	2	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-8000/801	Meter	2	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-8700DB/871DB	Dial	2	8v,300ma	0500710	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-8700DB/871DB	Dial	2	8v,150ma	0400660	
Sansui	G-9000/901	Dial	2	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-9000/901	Meter	2	8v,300ma	0400560	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-9700/971	Dial	2	8v,300ma	0500710	10mm globe bulb in rubber grommet base with 2 wires.
Sansui	G-9700/971	Dial	2	8v,150ma	0400660	
Sansui	TA-500	Dial + Meters	2	8v,300ma		10mm globe bulb in rubber grommet base with 2 wires.
Sansui	TA-500	Dial + Meters	2	8v,300ma		10mm globe bulb in rubber grommet base with 2 wires.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Sansui	TU-317	Dial + Meters	2	8v,300ma		10mm globe bulb in rubber grommet base with 2 wires.
Sansui	TU-417/507	Dial + Meters	4	8v,300ma		10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Kenwood KR-9600.
Sansui	TU-517	Dial + Meters	4	8v,300ma		10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Kenwood KR-9600.
Sansui	TU-519	Dial + Meters	2	8v,300ma		10mm globe bulb in rubber grommet base with 2 wires.
Sansui	TU-5900	Dial	5	8v,300ma		10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Kenwood KR-9600.
Sansui	TU-717/707	Dial + Meters	4	8v,300ma		10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Kenwood KR-9600.
Sansui	TU-719	Dial + Meters	2	8v,300ma		10mm globe bulb in rubber grommet base with 2 wires.
Sansui	TU-7900	Dial	5	8v,300ma		10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Kenwood KR-9600.
Sansui	TU-919	Dial + Meters	2	8v,300ma		10mm globe bulb in rubber grommet base with 2 wires.

Make	Model	Function	# Lamps	Rating	Part #	Notes
Sansui	TU-9900	Dial	4	8v,300ma		10mm globe bulb. Marked "Stanley 8v, 0.3a".Rubber base slides over two pins. Same as Kenwood KR-9600.
Sansui	TU-9900	Meters	4	8v, ? ma		Small (4mm?) lamp with rubber base and two wires.